

Under development	
New product	●

GP1UM27XK series IR Detecting Unit for Remote Control

Compact IR Detecting Unit for Remote Control

■ Features

- (1) Compact
 - Outline dimensions: 5.6 × 9.6 × 6.8mm
(GP1UM26XK)
 - Mounting area: 44% reduction compared to conventional models
- (2) Low dissipation current
Dissipation current: MAX.1.5mA
- (3) Product lineup includes types with strengthened resistance to electromagnetic induction noise.
- (4) Profile variations enable flexible mounting.

■ Applications

- (1) AV equipment
- (2) Home appliances

■ Absolute Maximum Ratings

(Ta=25°C)


Parameter	Symbol	Ratings	Unit
Supply voltage	V _{cc}	6	V
*1 Operating temperature	T _{opr}	-10 to +70	°C
Storage temperature	T _{stg}	-20 to +70	°C
*2 Soldering temperature	T _{sol}	260	°C

*1 No dew formation

*2 For 5s

■ Outline Dimensions

(Unit: mm)



■ Recommended Operating Conditions

(Ta=25°C)

Parameter	Symbol	Ratings	Unit
Supply voltage	V _{cc}	4.5 to 5.5	V

(Notice)

•In the absence of confirmation by device specification sheets, SHARP takes no responsibility for any defects that may occur in equipment using any SHARP devices shown in catalogs, data books, etc. Contact SHARP in order to obtain the latest device specification sheets before using any SHARP device.

•Specifications are subject to change without notice for improvement.

(Internet)

•Data for Sharp's optoelectronic/power devices is provided on internet. (Address <http://sharp-world.com/ecg/>)

GP1UM27XK Series IR Detecting Unit for Remote Control

Electrical Characteristics

(Ta=25°C, Vcc=+5V)

Parameter	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Dissipation current	I _{CC}	No incident light, V _{CC} =3V	-	-	1.5	mA
High level output voltage	V _{OH}	-	V _{CC} - 0.5	-	-	V
Low level output voltage	V _{OL}	I _{OL} =1.6mA	-	-	0.5	V
B.P.F. center frequency	f _o	-	-	*3	-	kHz
Detecting distance	L	-	8	-	-	m

*3 B.P.F. center frequency for each model is shown in the list below.


Model Line-ups

Various B.P.F. frequencies matching with customers' requirements are also available.

B.P.F. frequencies	Model No.				
40kHz		GP1UM26XK	GP1UM27XK	GP1UM28XK	GP1UM28YK
	*	GP1UM26RK	GP1UM27RK	GP1UM28RK	GP1UM28QK
36kHz		GP1UM260XK	GP1UM270XK	GP1UM280XK	GP1UM280YK
	*	GP1UM260RK	GP1UM270RK	GP1UM280RK	GP1UM280QK
38kHz		GP1UM261XK	GP1UM271XK	GP1UM281XK	GP1UM281YK
	*	GP1UM261RK	GP1UM271RK	GP1UM281RK	GP1UM281QK
36.7kHz		GP1UM262XK	GP1UM272XK	GP1UM282XK	GP1UM282YK
	*	GP1UM262RK	GP1UM272RK	GP1UM282RK	GP1UM282QK
32.75kHz		GP1UM263XK	GP1UM273XK	GP1UM283XK	GP1UM283YK
	*	GP1UM263RK	GP1UM273RK	GP1UM283RK	GP1UM283QK
56.8kHz		GP1UM267XK	GP1UM277XK	GP1UM287XK	GP1UM287YK
		GP1UM267RK	GP1UM277RK	GP1UM287RK	GP1UM287QK

* Types with strengthened resistance to electromagnetic induction noise.

Block Diagram



As of September 2001

NOTICE

- The circuit application examples in this publication are provided to explain representative applications of SHARP devices and are not intended to guarantee any circuit design or license any intellectual property rights. SHARP takes no responsibility for any problems related to any intellectual property right of a third party resulting from the use of SHARP's devices.
- Contact SHARP in order to obtain the latest device specification sheets before using any SHARP device. SHARP reserves the right to make changes in the specifications, characteristics, data, materials, structure, and other contents described herein at any time without notice in order to improve design or reliability. Manufacturing locations are also subject to change without notice.
- Observe the following points when using any devices in this publication. SHARP takes no responsibility for damage caused by improper use of the devices which does not meet the conditions and absolute maximum ratings to be used specified in the relevant specification sheet nor meet the following conditions:
 - (i) The devices in this publication are designed for use in general electronic equipment designs such as:
 - Personal computers
 - Office automation equipment
 - Telecommunication equipment [terminal]
 - Test and measurement equipment
 - Industrial control
 - Audio visual equipment
 - Consumer electronics
 - (ii) Measures such as fail-safe function and redundant design should be taken to ensure reliability and safety when SHARP devices are used for or in connection with equipment that requires higher reliability such as:
 - Transportation control and safety equipment (i.e., aircraft, trains, automobiles, etc.)
 - Traffic signals
 - Gas leakage sensor breakers
 - Alarm equipment
 - Various safety devices, etc.
 - (iii) SHARP devices shall not be used for or in connection with equipment that requires an extremely high level of reliability and safety such as:
 - Space applications
 - Telecommunication equipment [trunk lines]
 - Nuclear power control equipment
 - Medical and other life support equipment (e.g., scuba).
- Contact a SHARP representative in advance when intending to use SHARP devices for any "specific" applications other than those recommended by SHARP or when it is unclear which category mentioned above controls the intended use.
- If the SHARP devices listed in this publication fall within the scope of strategic products described in the Foreign Exchange and Foreign Trade Control Law of Japan, it is necessary to obtain approval to export such SHARP devices.
- This publication is the proprietary product of SHARP and is copyrighted, with all rights reserved. Under the copyright laws, no part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, for any purpose, in whole or in part, without the express written permission of SHARP. Express written permission is also required before any use of this publication may be made by a third party.
- Contact and consult with a SHARP representative if there are any questions about the contents of this publication.